

Disassembly instruction



1
First step:remove the screw of the under damper.



2
Second step:pull PCB protection board out.




3
Third step:remove screws of the PCB box top cover.



4
Fourth step:open the PCB box top cover .



5
Fifth step:remove the screw of the PCB board.



6
Sixth step:take four white terminals down.




7
Seventh step:remove the screw of the net cover.




8
Eighth step:remove the screw of the aluminium cover.



9
Ninth step:remove the screw of the under damper.



10
Tenth step:pull 2096-S safe net out.




11
Eleventh step:open the ear wire clasp with tweezers.



12
Twelfth step:pull the wire's terminal out.




13
Thirteenth step:pull the two wires to see black silicone.




14
Fourteenth step:remove the black silicone.




15
After removed the black silicone,see the terminal block.




16
After pulled the two wires to see black silicone,see the terminal block.




17
Fifteenth step:separate the two connecting terminal block.



18
Sixteenth step:pull four cables out.



19
Seventeenth step:pull strands of wire casing out.



20
Eighteenth step:unplug the wire terminals .



21
Nineteenth step:loosen the heating element clamp.



22
Twentieth step:two hands hold the heating element clamp.



23
Twenty-first step:pull the heating element 1 out.



24
Twenty-second step:pull the heating element 1 out.



25
Heating element 1 removed completely



26
Twenty-third step:repeat nineteenth,twentieth,twenty-first step,pull the heating element 2 out.